

Amendments to the Claims:

This listing of claims will replace all prior versions, and listings, of claims in the application:

Listing of Claims:

1. (Currently amended) A method for adapting to changes affecting a wireless signal comprising:

detecting ~~an amount of motion~~ a movement of a communication device communicating the wireless signal or an external object in a signal path based on a measurement of a metric of a modulated signal attribute comprised of at least one of amplitude, frequency, and phase;

selecting a parameter adjustment, based on the detected ~~motion~~ movement, of at least one of: an antenna mode, a power level, a forward error correction (FEC) coding rate, a number of modulation symbols, and a data transfer rate; and

performing the parameter adjustment.

2. (Previously presented) The method as in Claim 1, wherein the detecting is performed by a mobile station.

Claims 3. and 4. (Canceled).

5. (Previously presented) The method as in Claim 1, wherein the detecting is based on a signal in an automatic gain control (AGC) loop.

6. (Previously presented) The method as in Claim 5, wherein the detecting is a function of a statistic of the signal in the AGC loop.

7. (Previously presented) The method as in Claim 6, wherein the statistic that is used is variance.

8. (Previously presented) The method as in Claim 1, wherein the detecting is based on a phase error signal produced by at least one of a delay lock loop, matched filter, or correlator.

9. (Previously presented) The method as in Claim 8, wherein the detecting is a function of a statistic of the phase error signal.

10. (Previously presented) The method as in Claim 9, wherein the statistic that is used is variance.

11. (Previously presented) The method as in Claim 1, wherein the metric is based on a frequency error signal in a frequency control loop.

12. (Previously presented) The method as in Claim 11, wherein the detecting is a function of a statistic of the frequency error signal.

13. (Previously presented) The method as in Claim 12, wherein the statistic that is used is variance.

14. (Previously presented) The method as in Claim 1, wherein the detecting includes:

comparing the metric to a threshold level.

Claim 15. (Canceled).

16. (Previously presented) The method as in Claim 1, wherein the selecting the parameter adjustment includes selecting the antenna mode comprises changing from directive to omni-directional.

17. (Previously presented) The method as in Claim 1, wherein the selecting the parameter adjustment includes selecting the antenna mode comprises changing from omni-directional to directive.

Claim 18. (Canceled).

19. (Previously presented) The method as in Claim 1, wherein the selecting the parameter adjustment includes selecting to reduce at least one of the FEC coding rate, or the number of modulation symbols, to a minimum level while maintaining the signal path.

Claim 20. (Canceled).

21. (Currently amended) An apparatus for adapting to changes affecting a wireless signal, comprising:

a processing unit configured to detect ~~an amount of motion~~ a movement of a communication device communicating the wireless signal or an external object in a signal path based on a measurement of a metric of a modulated signal attribute comprised of at least one of amplitude, frequency, or phase; and

a compensator configured to make a signaling parameter adjustment, responsive to ~~motion~~ the movement detected by the processing unit, of at least one of an antenna mode, a forward error correction (FEC) coding rate, a number of modulation symbols, and a data transfer rate.

22. (Previously presented) The apparatus as in Claim 21, configured as a mobile station.

Claims 23. and 24. (Canceled).

25. (Previously presented) The apparatus as in Claim 21, wherein the processing unit is configured to detect motion based on a signal in an automatic gain control (AGC) loop.

26. (Previously presented) The apparatus as in Claim 25, wherein the processing unit is configured to detect motion as a function of a statistic of the signal in the AGC loop.

27. (Previously presented) The apparatus as in Claim 26, wherein the processing unit is configured to use variance as the statistic.

28. (Previously presented) The apparatus as in Claim 21, wherein the processing unit is configured to detect motion based on a phase error signal produced by at least one of a delay lock loop, a matched filter, or a correlator.

29. (Previously presented) The apparatus as in Claim 28, wherein the processing unit is configured to detect motion as a function of a statistic of the phase error signal.

30. (Previously presented) The apparatus as in Claim 29, wherein the processing unit is configured to use variance as the statistic.

31. (Previously presented) The apparatus as in Claim 21, wherein the processing unit is configured to detect motion based on a frequency error signal in a frequency control loop.

32. (Previously presented) The apparatus as in Claim 31, wherein the processing unit is configured to detect motion as a function of a statistic of the frequency error signal.

33. (Previously presented) The apparatus as in Claim 32, wherein the processing unit is configured to use variance as the statistic.

34. (Previously presented) The apparatus as in Claim 21, wherein the processing unit is configured to detect motion using a comparison threshold level.

35. (Previously presented) The apparatus as in Claim 21, further comprising:

an antenna having a changeable antenna mode, wherein the compensator is configured to change the antenna mode.

36. (Previously presented) The apparatus as in Claim 35, wherein the compensator is configured to change the antenna mode between directive and omnidirectional modes.

Claim 37. (Canceled).

Claim 38. (Canceled).

39. (Previously presented) The apparatus as in Claim 21, wherein the compensator is configured to reduce at least one of the FEC coding rate, or the number of modulation symbols, to a minimum level while maintaining the signal path.

Claims 40. and 41. (Canceled).

42. (Currently amended) A computer-readable storage medium containing a set of instructions for a general purpose computer, the set of instructions comprising:

a signal adaptation code segment configured to cause a processor to control a signaling path to adapt to changes affecting the signaling path,

a detection code segment configured to detect ~~an amount of motion a~~ movement of a communication device communicating the wireless signal or an external object in a signal path based on a measurement of a metric of a modulated signal attribute comprised of at least one of amplitude, frequency, and phase; and

an adjusting code segment configured to make a signaling parameter adjustment, responsive to ~~motion~~ the movement detected by the detecting code segment, of at least one of an antenna mode, a forward error correction (FEC) coding rate, a number of modulation symbols, and a data transfer rate.